



On Some Lag Synchronization and Higher Order Parabolic Systems

Khairia El-Said El-Nadi, Wagdy G. Elsayed, Mabroka F. Bader

Department of Mathematics and Computer Science, Faculty of Science, Alexandria University, Alexandria, Egypt

Email address:

khairia_el_said@hotmail.com (K. El-Said El-Nadi), Wagdygoma@alexu.edu.eq (W. G. Elsayed), m.bader.f1986@gmail.com (M. F. Bader)

To cite this article:

Khairia El- Said El-Nadi, Wagdy G. Elsayed, Mabroka F. Bader. On Some Lag Synchronization and Higher Order Parabolic Systems.

American Journal of Theoretical and Applied Statistics. Special Issue: Statistical Distributions and Modeling in Applied Mathematics.

Vol. 6, No. 5-1, 2017, pp. 23-29. doi: 10.11648/j.ajtas.s.2017060501.14

Received: March 7, 2017; **Accepted:** March 8, 2017; **Published:** March 20, 2017

Abstract: Chaos synchronization is a topic of great interest, due to its observation in a huge variety of phenomena of different nature. We study synchronization of two chaotic oscillators in a Master- Slave configuration. The two dynamic systems are coupled via a directed feedback that randomly switches among a finite set of given constant function at a prescribed time rate. And we use Lyapunov stability theory. This paper discussed the using of lag synchronization approach, and provided the equilibrium solutions of a new class of higher order parabolic partial differential equations to be applicable for Lorenz chaotic system in order to minimize the dynamical error of large Lorenz chaotic system

Keywords: Higher Order Parabolic Partial Differential Equations, Lag Synchronization, Adaptive Technique, Lorenz Chaotic System

1. Introduction

Chaotic systems provide a rich mechanism for signal design and generation, with potential applications to communications and signal processing, because chaotic signals are typically broad band, noise like, and difficult to predict they can be used in various contexts for masking information bearing wave forms.

The early work on chaos synchronization was reported by Pecora and Carroll [1], in the derive-response systems. Chaos synchronization is an interesting nonlinear phenomenon have been attracted extremely attention due its possible implementation in many workable engineering domains, and dynamical systems. For examples secure connection [2], information processing [3], and so on. There are many reported schemes for chaos synchronization including non linear feed back approach [4, 5], adaptive technique [6], back stepping method [7], impulsive control method [8], etc.

Recently different types of synchronization were studied including: complete synchronization [9], generalized synchronization [10], phase synchronization [11], lag synchronization [12], dislocated synchronization [13]. In this paper, we generalize some results about the lag synchronization of Lorenz chaotic system with uncertain

parameters by considering higher order parabolic equations as follows:

This work aims to minimize the synchronization error in the dynamical systems by finding suitable controller, and coefficients for these systems. See [14-16]

2. Parabolic synchronization

Consider the following chaotic system (1), and (2).

$$\frac{\partial u_1(x,t)}{\partial t} = \sum_{|q| \leq 2M} a_q(x) D^q u_1(x,t) + \alpha[u_2(x,t) - u_1(x,t)] \quad (1)$$

$$\frac{\partial u_2(x,t)}{\partial t} = \sum_{|q| \leq 2M} b_q(x) D^q u_2(x,t) + [u_1(x,t)u_2(x,t) - \beta u_2(x,t)] \quad (2)$$

$$\frac{\partial u_3(x,t)}{\partial t} = \sum_{|q| \leq 2M} c_q(x) D^q u_3(x,t) + [\delta u_1(x,t) - u_1(x,t)u_3(x,t) - u_3(x,t)] \quad (3)$$

Where:

$$U_i(x, 0) = \varphi_i(x), i = 1, 2, 3$$

$\varphi_1, \varphi_2, \varphi_3$ are bounded continuous functions on R^n and $x = (x_1, x_2, \dots, x_n) \in R^n, R^n$ is the

n-dimensional Euclidean space,

$$D^q = D_1^{q_1} \dots D_n^{q_n}, D_j = \frac{\partial}{\partial x_j}$$

($q = (q_1, \dots, q_n)$ is an n-dimensional multi-index, $|q| = q_1 + q_2 + \dots + q_n$

and a_q, b_q, c_q are continuous bounded function defined on R^n for all $q \leq 2M$.

It is assumed that the operators:

$$\sum_{|q| \leq 2M} a_q(x) D^q, \sum_{|q| \leq 2M} b_q(x) D^q, \sum_{|q| \leq 2M} c_q(x) D^q$$

are strictly parabolic.. This means that:

$$\sum_{|q| \leq 2M} a_q(x) y^q \geq \delta |y|^{2M}, \sum_{|q| \leq 2M} b_q(x) y^q \geq \delta |y|^{2M},$$

$$\sum_{|q| \leq 2M} c_q(x) y^q \geq \delta |y|^{2M} \text{ for all } x \in R^n, \text{ where}$$

$$y = (y_1, \dots, y_n), |y|^2 = y_1^2 + \dots + y_n^2,$$

where δ is a positive constant [17].

Let us consider the following second chaotic system:

$$\begin{aligned} \frac{\partial v_1(x, t)}{\partial t} &= \sum_{|q| \leq 2M} a_q(x) D^q v_1(x, t) \\ &\quad + \alpha_s [v_2(x, t) - v_1(x, t)] + w_1(x, t) \\ \frac{\partial v_2(x, t)}{\partial t} &= \sum_{|q| \leq 2M} b_q(x) D^q v_2(x, t) \\ &\quad + [v_1(x, t)v_2(x, t) + \beta_s v_2(x, t)] + w_2(x, t) \\ \frac{\partial v_3(x, t)}{\partial t} &= \sum_{|q| \leq 2M} c_q(x) D^q v_3(x, t) + [\delta_s v_1(x, t) \\ &\quad - v(x, t)v_3(x, t) - v_3(x, t)] \\ &\quad + w_3(x, t) \end{aligned} \quad (2)$$

Where α_s, β_s , and δ_s of (2) are unknown coefficients, we have:

$$\begin{aligned} u_1(x, t) &= \int_{R^n} G_1(x, y, t) u_1(y) dy + \\ &\quad \alpha \int_0^t \int_{R^n} G_1(x, y, t - \theta) [u_2(y, \theta) \\ &\quad - u_1(y, \theta)] dy d\theta, \end{aligned}$$

$$u_2(x, t) = \int_{R^n} G_2(x, y, t) u_2(y) dy +$$

$$\int_0^t \int_{R^n} G_2(x, y, t - \theta) [u_1(y, \theta)u_2(y, \theta) - \beta u_2(y, \theta)] dy d\theta$$

$$u_3(x, t) = \int_{R^n} G_3(x, y, t) u_3(y) dy +$$

$$\int_0^t \int_{R^n} G_3(x, y, t - \theta) [\delta u_1(y, \theta) - u_1(y, \theta)u_3(y, \theta) - u_3(y, \theta)] dy d\theta$$

Where $G_i(x, y, t), i = 1, 2, 3$, and G_1, G_2, G_3 is the fundamental solutions of the following problems: see [18-23]

$$\frac{\partial V_i(x, t)}{\partial t} = L_i(x, t, D) V_i$$

Where: $L_1(x, t, D) = \sum a_q(x) D^q$, $L_2(x, t, D) = m \sum b_q(x) D^q$, and

$$L_3(x, t, D) = \sum c_q(x) D^q$$

$$\text{Let: } u_i^*(x, t) = \int_{R^n} G_i(x, y, t) u_i(y) dy$$

It is easy to see that:

$$u_1(x, t) = u_1^*(x, t) + \alpha \int_0^t \int_{R^n} G_1(x, y, t - \theta) [u_2(y, \theta) - u_1(y, \theta)] dy d\theta,$$

$$u_2(x, t) = u_2^*(x, t) + \int_0^t \int_{R^n} G_2(x, y, t - \theta) [u_1(y, \theta)u_2(y, \theta) - \beta u_2(y, \theta)] dy d\theta,$$

$$\begin{aligned} u_3(x, t) &= \\ &u_3^*(x, t) + \\ &\alpha \int_0^t \int_{R^n} G_3(x, y, t - \theta) [\delta u_1(y, \theta) - u_1(y, \theta)u_3(y, \theta) - u_3(y, \theta)] dy d\theta, \end{aligned}$$

Now we have:

$$\frac{\partial u_1(x, t)}{\partial t} = \frac{\partial}{\partial t} u_1^*(x, t) + \alpha [u_2(x, t) - u_1(x, t)]$$

$$\alpha \int_0^t \int_{R^n} \frac{\partial}{\partial t} G_1(x, y, t - \theta) [u_2(y, \theta) - u_1(y, \theta)] dy d\theta$$

$$\begin{aligned} \frac{\partial u_2(x, t)}{\partial t} &= \frac{\partial}{\partial t} u_2^*(x, t) + [u_1(x, t)u_2(x, t) - \beta u_2(x, t)] + \\ &\quad \int_0^t \int_{R^n} \frac{\partial}{\partial t} G_2(x, y, t - \theta) [u_1(y, \theta)u_2(y, \theta) \\ &\quad - \beta u_2(y, \theta)] dy d\theta \end{aligned}$$

$$-\beta u_2(y, \theta)] dy d\theta$$

$$\begin{aligned} \frac{\partial u_3(x, t)}{\partial t} &= \frac{\partial}{\partial t} u_3^*(x, t) + [\delta u_1(x, t) - u_1(x, t)u_3(x, t) \\ &\quad - u_3(x, t)] + \end{aligned}$$

$$\begin{aligned} &\int_0^t \int_{R^n} \frac{\partial}{\partial t} G_3(x, y, t - \theta) [\delta u_1(y, \theta) - \\ &\quad - u_1(y, \theta)u_3(y, \theta) - u_3(y, \theta)] dy d\theta. \end{aligned}$$

Let:

$$\begin{aligned}f_1(x, t) &= \int_0^L \int_{R^n} G_1(x, y, t - \theta) f_1(x, t) dx dt \\f_2(x, t) &= \int_0^L \int_{R^n} G_2(x, y, t - \theta) f_2(x, t) dx dt \\f_3(x, t) &= \int_0^L \int_{R^n} G_3(x, y, t - \theta) f_3(x, t) dx dt\end{aligned}$$

Now considering the following chaotic Parabolic system (1), and (2) see [24-38]

$$\begin{aligned}\frac{\partial u_1(x, t)}{\partial t} &= \frac{\partial u_1^*(x, t)}{\partial t} + \alpha [u_2(x, t) - u_1(x, t)] + \frac{\partial f_1(x, t)}{\partial t}, \\ \frac{\partial u_2(x, t)}{\partial t} &= \frac{\partial u_2^*(x, t)}{\partial t} + [u_1(x, t)u_2(x, t) - \beta u_2(x, t)] + \frac{\partial f_2(x, t)}{\partial t}, \\ \frac{\partial u_3(x, t)}{\partial t} &= \frac{\partial u_3^*(x, t)}{\partial t} + [\delta u_1(x, t) - u_1(x, t)u_3(x, t) \\ &\quad - u_3(x, t) + \frac{\partial f_3(x, t)}{\partial t}].\end{aligned}$$

and

$$\begin{aligned}\frac{\partial v_1(x, t)}{\partial t} &= \frac{\partial v_1^*(x, t)}{\partial t} + \alpha_s [v_2(x, t) - v_1(x, t)] \\ &\quad + \frac{\partial g_1(x, t)}{\partial t} + w_1(x, t) \\ \frac{\partial v_2(x, t)}{\partial t} &= \frac{\partial v_2^*(x, t)}{\partial t} + [v_1(x, t)v_2(x, t) - \beta_s v_2(x, t)] \\ &\quad + \frac{\partial g_2(x, t)}{\partial t} + w_2(x, t), \\ \frac{\partial v_3(x, t)}{\partial t} &= \frac{\partial v_3^*(x, t)}{\partial t} + [\delta_s v_1(y, t) - v_1(y, t)v_3(y, t) \\ &\quad - v_3(x, t) + \frac{\partial g_3(x, t)}{\partial t} + w_3(x, t)]\end{aligned}$$

Where:

$$\begin{aligned}\frac{\partial f_1(x, t)}{\partial t} &= \alpha \int_0^t \int_{R^n} \frac{\partial}{\partial t} \partial G_1(x, y, t - \theta) \cdot [u_2(y, \theta) \\ &\quad - u_1(y, \theta)] dy d\theta, \\ \frac{\partial f_2(x, t)}{\partial t} &= \int_0^t \int_{R^n} \frac{\partial}{\partial t} \partial G_2(x, y, t - \theta) \\ &\quad [u_1(y, \theta)u_2(y, \theta) - \beta u_2(y, \theta)] dy d\theta, \\ \frac{\partial f_3(x, t)}{\partial t} &= \int_0^t \int_{R^n} \frac{\partial}{\partial t} \partial G_3(x, y, t - \theta) \\ &\quad [\delta u_1(y, \theta) - u_1(y, \theta)u_3(y, \theta) \\ &\quad - u_3(y, \theta)] dy d\theta, \\ \frac{\partial g_1(x, t)}{\partial t} &= \alpha_s \int_0^t \int_{R^n} \frac{\partial}{\partial t} G_1(x, y, t - \theta) \cdot [v_2(y, \theta) \\ &\quad - v_1(y, \theta)] dy d\theta, \\ \frac{\partial g_2(x, t)}{\partial t} &= \int_0^t \int_{R^n} \frac{\partial}{\partial t} G_2(x, y, t - \theta)\end{aligned}$$

$$\begin{aligned}[v_1(y, \theta) v_2(y, \theta) - \beta_s v_2(y, \theta)] dy d\theta, \\ \frac{\partial g_3(x, t)}{\partial t} = \int_0^t \int_{R^n} \frac{\partial}{\partial t} G_3(x, y, t - \theta) \\ [\delta_s v_1(y, \theta) - v_1(y, \theta)v_3(y, \theta) \\ - v_3(y, \theta)] dy d\theta.\end{aligned}$$

Where α_s, β_s , and δ_s are unknown coefficients. Let:

$$\begin{aligned}e_1(x, t) &= v_1(x, t) - u_1(x, t - \tau) \\ e_2(x, t) &= v_2(x, t) - u_2(x, t - \tau) \\ e_3(x, t) &= v_3(x, t) - u_3(x, t - \tau)\end{aligned}\quad (3)$$

Where $t > 0$ is the time delay of the errors dynamical system. Now the goal of the parameters identified, and lag synchronization is to find an appropriate controller $W(x, t)$, and parameter adaptive laws of α_s, β_s , and δ_s such that the synchronization errors

$$e_1(x, t) \rightarrow 0, e_2(x, t) \rightarrow 0, e_3(x, t) \rightarrow 0 \quad (4)$$

as $t \rightarrow 0$, and the unknown coefficients satisfy the conditions:

$$\lim_{t \rightarrow \infty} \alpha_s = \alpha, \lim_{t \rightarrow \infty} \beta_s = \beta, \lim_{t \rightarrow \infty} \delta_s = \delta \quad (5)$$

Remark 1: When $\tau > 0$, the lag synchronization will appear, when $\tau < 0$, the anticipated synchronization will appear. Generally complete synchronization will appear

$$\text{when, } \tau = 0.$$

Remark 2: For the anticipated synchronization, and complete synchronization. The discussions are similar to the method given in this paper.

3. Adaptive Lag Synchronization of Lorenz Chaotic System

$$\begin{aligned}\frac{\partial e_1(x, t)}{\partial t} &= \frac{\partial v_1(x, t)}{\partial t} - \frac{\partial u_1(x, t - \tau)}{\partial t} \\ \frac{\partial e_1(x, t)}{\partial t} &= \frac{\partial v_1^*(x, t)}{\partial t} + \alpha_s v_2(x, t) - \alpha_s v_1(x, t) \\ &\quad + \frac{\partial g_1(x, t)}{\partial t} + w_1(x, t) \\ \frac{\partial u_1^*(x, t - \tau)}{\partial t} - \alpha u_2(x, t - \tau) + \alpha u_1(x, t - \tau) - \frac{\partial f_1(x, t)}{\partial t} \\ \frac{\partial e_1(x, t)}{\partial t} &= \frac{\partial e_1^*(x, t)}{\partial t} + \alpha_s v_2(x, t) - \alpha_s v_1(x, t) + \frac{\partial g_1(x, t)}{\partial t} + w_1(x, t) - \\ &\quad \alpha u_2(x, t - \tau) + \alpha u_1(x, t - \tau) - \frac{\partial f_1(x, t)}{\partial t} \\ \frac{\partial e_1(x, t)}{\partial t} &= \frac{\partial e_1^*(x, t)}{\partial t} + \alpha_s v_2(x, t) - \alpha_s v_1(x, t) + \frac{\partial g_1(x, t)}{\partial t} + w_1(x, t) - \\ &\quad \alpha u_2(x, t - \tau) + \alpha u_1(x, t - \tau) - \alpha v_1(x, t - \tau) + \\ &\quad \alpha v_1(x, t) - \frac{\partial f_1(x, t)}{\partial t} \\ \dot{e}_1(x, t) &= \frac{\partial e_1^*(x, t)}{\partial t} - \alpha e_1(x, t) + \alpha_s v_2(x, t)\end{aligned}$$

$$\begin{aligned}
& -(\alpha_s - \alpha)v_1(x, t) + \frac{\partial g_1(x, t)}{\partial t} + \\
& w_1(x, t) - \alpha u_2(x, t - \tau) - \frac{\partial f_1(x, t)}{\partial t} \\
& \frac{\partial e_2(x, t)}{\partial t} = \frac{\partial v_2(x, t)}{\partial t} - \frac{\partial u_2(x, t - \tau)}{\partial t} \\
& \frac{\partial e_2(x, t)}{\partial t} = \frac{\partial v_2^*(x, t)}{\partial t} + v_1(x, t)v_2(x, t) - \beta_s v_2(x, t) + \\
& \frac{\partial g_2(x, t)}{\partial t} + w_2(x, t) - \\
& - \frac{\partial u_2^*(x, t - \tau)}{\partial t} - u_1(x, t - \tau)u_2(x, t - \tau) + \beta u_2(x, t - \tau) - \\
& \frac{\partial f_2(x, t)}{\partial t} \\
& \frac{\partial e_2(x, t)}{\partial t} = \frac{\partial e_2^*(x, t)}{\partial t} + v_1(x, t)v_2(x, t) \\
& - \beta_s v_2(x, t) + \frac{\partial g_2(x, t)}{\partial t} + w_2(x, t) - u_1(x, t - \tau)u_2(x, t - \tau) + \beta u_2(x, t - \tau) \\
& \frac{\partial f_2(x, t)}{\partial t} \\
& \frac{\partial e_2(x, t)}{\partial t} = \frac{\partial e_2^*(x, t)}{\partial t} + v_1(x, t)v_2(x, t) \\
& - \beta_s v_2(x, t) + \frac{\partial g_2(x, t)}{\partial t} + w_2(x, t) + \beta v_2(x, t) - \beta v_2(x, t) \\
& - u_1(x, t - \tau)u_2(x, t - \tau) + \beta u_2(x, t - \tau) - \frac{\partial f_2(x, t)}{\partial t} \\
& \frac{\partial e_2(x, t)}{\partial t} = \frac{\partial e_2^*(x, t)}{\partial t} + v_1(x, t)v_2(x, t) \\
& - (\beta_s - \beta)v_2(x, t) + \frac{\partial g_2(x, t)}{\partial t} \\
& + w_2(x, t) - \beta[v_2(x, t) - u_2(x, t - \tau)] - u_1(x, t - \tau)u_2(x, t - \tau) - \frac{\partial f_2(x, t)}{\partial t} \\
& \dot{e}_2(x, t) = \frac{\partial e_2^*(x, t)}{\partial t} + v_1(x, t)v_2(x, t) \\
& - (\beta_s - \beta)v_2(x, t) + \frac{\partial g_2(x, t)}{\partial t} + w_2(x, t) - \beta e_2(x, t) - \\
& u_1(x, t - \tau)u_2(x, t - \tau) - \frac{\partial f_2(x, t)}{\partial t} \\
& \frac{\partial e_3(x, t)}{\partial t} = \frac{\partial v_3(x, t)}{\partial t} - \frac{\partial u_3(x, t - \tau)}{\partial t} \\
& \frac{\partial e_3(x, t)}{\partial t} = \frac{\partial v_3^*(x, t)}{\partial t} + \delta_s v_1(x, t) - v_1(x, t) \\
& v_3(x, t) - v_3(x, t) + \frac{\partial g_3(x, t)}{\partial t} + w_3(x, t) \\
& - \frac{\partial u_3^*(x, t - \tau)}{\partial t} - \delta u_1(x, t - \tau) + u_1(x, t - \tau)u_3(x, t - \tau) + \\
& u_3(x, t - \tau) - \frac{\partial f_3(x, t)}{\partial t} \\
& \frac{\partial e_3(x, t)}{\partial t} = \frac{\partial e_3^*(x, t)}{\partial t} + \delta_s v_1(x, t) - v_1(x, t)v_3(x, t) - \\
& v_3(x, t) - u_3(x, t) + \frac{\partial g_3(x, t)}{\partial t} + w_3(x, t) - \\
& \frac{\partial e_3(x, t)}{\partial t} = \frac{\partial e_3^*(x, t)}{\partial t} + (\delta_s - \delta)v_1(x, t)v_3(x, t) - \\
& [v_1(x, t)v_3(x, t)] - \\
& - v_3(x, t) - u_3(x, t) + \frac{\partial g_3(x, t)}{\partial t} + w_3(x, t) - \\
& - \delta u_1(x, t - \tau) + u_3(x, t - \tau) - \frac{\partial f_3(x, t)}{\partial t} + \delta v_1(x, t) \\
& e_3(x, t) = \frac{\partial e_3^*(x, t)}{\partial t} - (\delta_s - \delta)v_1(x, t) - v_1(x, t)v_3(x, t) - \\
& e_3(x, t) + \frac{\partial g_3(x, t)}{\partial t} + w_3(x, t) - \delta u_1(x, t - \tau) + \\
& u_1(x, t - \tau)u_3(x, t - \tau) - \frac{\partial f_3(x, t)}{\partial t} + \delta v_1(x, t)
\end{aligned}$$

We have the error dynamical system.

$$\begin{aligned}
\dot{e}_1(x, t) &= \frac{\partial e_1^*(x, t)}{\partial t} - \alpha e_1(x, t) + \alpha_s v_2(x, t) \\
& - (\alpha_s - \alpha)v_1(x, t) + \frac{\partial g_1(x, t)}{\partial t} + \\
& w_1(x, t) - \alpha u_2(x, t - \tau) - \frac{\partial f_1(x, t)}{\partial t} \quad (6)
\end{aligned}$$

$$\begin{aligned}
\dot{e}_2(x, t) &= \frac{\partial e_2^*(x, t)}{\partial t} + v_1(x, t)v_2(x, t) \\
& - (\beta_s - \beta)v_2(x, t) + \frac{\partial g_2(x, t)}{\partial t} + w_2(x, t) - \beta e_2(x, t) \\
& - u_1(x, t - \tau)u_2(x, t - \tau) - \frac{\partial f_2(x, t)}{\partial t} \\
& \dot{e}_3(x, t) = \frac{\partial e_3^*(x, t)}{\partial t} + (\delta_s - \delta)v_1(x, t) - v_1(x, t)v_3(x, t) - \\
& e_3(x, t) + \frac{\partial g_3(x, t)}{\partial t} + w_3(x, t) - \delta u_1(x, t - \tau) + \\
& u_1(x, t - \tau)u_3(x, t - \tau) - \frac{\partial f_3(x, t)}{\partial t} + \delta v_1(x, t)
\end{aligned}$$

It is clear that lag synchronization of system (1), and (2) appears if the dynamical errors (6) have stable equilibrium point, and converge to zero ($e(x, t) = 0$)

Where: $e(x, t) = [e_1(x, t), e_2(x, t), e_3(x, t)]^T$

Then the following theorem was obtained:

Assuming that Lorenz chaotic system (2) take:

$$\begin{aligned}
w_1(x, t) &= -\frac{\partial e_1^*(x, t)}{\partial t} - \alpha_s v_2(x, t) - \frac{\partial g_1(x, t)}{\partial t} + \alpha u_2(x, t - \tau) + \frac{\partial f_1(x, t)}{\partial t} \\
w_2(x, t) &= -\frac{\partial e_2^*(x, t)}{\partial t} - v_1(x, t)v_2(x, t) - \frac{\partial g_2(x, t)}{\partial t} \\
& + u_1(x, t - \tau)u_2(x, t - \tau) + \frac{\partial f_2(x, t)}{\partial t} \\
w_3(x, t) &= -\frac{\partial e_3^*(x, t)}{\partial t} + v_1(x, t)v_3(x, t) - \frac{\partial g_3(x, t)}{\partial t} \quad (7) \\
& + \delta u_1(x, t - \tau) - u_1(x, t - \tau)u_3(x, t - \tau) + \frac{\partial f_3(x, t)}{\partial t} - \delta v_1(x, t)
\end{aligned}$$

And parameter adaptive laws.

$$\begin{aligned}\alpha_s &= v_1(x, t)e_1(x, t) \\ \beta_s &= v_2(x, t)e_2(x, t) \\ \delta_s &= -v_1(x, t)e_3(x, t)\end{aligned}\tag{8}$$

Both the systems (1, and (2) could realize lag synchronization, and the unknown coefficients will be identified, i. e. equations (4), and (5) will be achieved.

Proof:

Equation (6) can be converted to the following form under the controller (7).

$$\begin{aligned}\dot{e}_1(x, t) &= -\alpha e_1(x, t) - (\delta_s - \delta) v_1(x, t) \\ \dot{e}_2(x, t) &= -\beta e_2(x, t) - (\beta_s - \beta) v_2(x, t) \\ \dot{e}_3(x, t) &= -e_3(x, t) + (\delta_s - \delta) v_1(x, t)\end{aligned}\tag{9}$$

Consider A Lyapunov function as:

$$V = \frac{1}{2} [e_1^2(x, t) + e_2^2(x, t) + e_3^2(x, t) + (\alpha_s - \alpha)^2 + (\beta_s - \beta)^2 + (\delta_s - \delta)^2]$$

It is clear that, V is a positive definite function. Taking its time derivative along with the trajectories of equation (8), and (9) leads to

$$\begin{aligned}\dot{V} &= e_1(x, t)\dot{e}_1(x, t) + e_2(x, t)\dot{e}_2(x, t) + e_3(x, t)\dot{e}_3(x, t) + \\ &\quad + (\alpha_s - \alpha)\dot{\alpha}_s + (\beta_s - \beta)\dot{\beta}_s + (\delta_s - \delta)\dot{\delta}_s \\ \dot{V} &= e_1(x, t) [-\alpha e_1(x, t) - (\alpha_s - \alpha)v_1(x, t)] + e_2(x, t) \\ &\quad [-\beta e_2(x, t) - (\beta_s - \beta)v_2(x, t)] + \\ &\quad e_3(x, t) [-e_3(x, t) - (\delta_s - \delta)v_1(x, t)] \\ &\quad + (\alpha_s - \alpha) \\ &\quad [v_1(x, t)e_1(x, t)] + (\beta_s - \beta)[v_2(x, t)e_2(x, t)] + \\ &\quad (\delta_s - \delta)[-v_1(x, t)e_3(x, t)] \\ \dot{V} &= -\alpha e_1^2(x, t) - \beta e_2^2(x, t) - e_3^2(x, t) \\ &= -e^t P_e \leq 0\end{aligned}$$

Where $P = \text{diag}\{\alpha, 1, \beta\}$. It is clear that

$\dot{V} = 0$ if and only if $e_i(x, t) = 0, \forall i = 1, 2, 3$

Namely the set:

$$Q = \left\{ \begin{array}{l} e_1(x, t) = 0, e_2(x, t) = 0, e_3(x, t) = 0, \\ \alpha_s = \alpha, \beta_s = \beta, \delta_s = \delta \end{array} \right\}$$

Is the largest invariant set contained in $E = \{\dot{v} = 0\}$

From equation (9), so according to the La Salles

Invariance principle [39]. Starting with arbitrary initial values of equation (9), the trajectory converges asymptotically to the set Q, i.e.

$e_1(x, t) \rightarrow 0, e_2(x, t) \rightarrow 0, e_3(x, t) \rightarrow 0$ as

$(\alpha_s \rightarrow \alpha, \beta_s \rightarrow \beta)$, and $(\delta_s \rightarrow \delta)$

As $t \rightarrow \infty$

This indicates that the lag synchronization of Lorenz chaotic system is achieved, and the unknown coefficients: $(\alpha_s, \beta_s, \delta_s)$

Can be successfully identified by using controller (7), and the parameter adaptive law (8). (Comp [40–44])

Acknowledgments

We would like to thank the referees for their careful reading of the paper and their valuable comments.

References

- [1] L. M. Pecora and T. L. Carroll, "Synchronization in Chaotic Systems," Physical Review Letters, Vol. 64, No. 8, 1990, pp. 821-824. doi:10.1103/PhysRevLett.64.821 [Citation Time(s):1].
- [2] Z. Li and D. Xu, "A Secure Communication Scheme using Projective Chaos Synchronization," Chaos, Solitons & Fractals, Vol. 22, No. 2, 2004, pp. 477-481. doi:10.1016/j.chaos.2004.02.019 [Citation Time(s):1].
- [3] C. Ling, X. Wu and S. Sun, "A General Efficient Method for Chaotic Signal Estimation," IEEE Transactions on Signal Processing, Vol. 47, No. 5, 1999, pp. 1424-1428. doi:10.1109/78.757236 [Citation Time(s):1].
- [4] H. A. Qais and A. A. Aouda, "Image Encryption Based on the General Approach for Multiple Chaotic Systems," Journal of Signal and Information Processing, Vol. 2, No. 3, 2011, pp. 238-244. [Citation Time(s):1].
- [5] F. Wang and C. Liu, "A New Criterion for Chaos and Hyperchaos Synchronization Using Linear Feedback Control," Physics Letters A, Vol. 360, No. 2, 2006, pp. 274-278. doi:10.1016/j.physleta.2006.08.037.
- [6] Z. Jia, J. A. Lu, and G. M. Deng, "Nonlinear State Feedback and Adaptive Synchronization of Hyperchaotic Lü Systems," Systems Engineering and Electronics, Vol. 29, No. 4, 2007, pp. 598-600. [Citation Time(s):1].
- [7] M. T. Yassen, "Controlling, Synchronization and Tracking Chaotic Liu System using Active Backstepping Design," Physics Letters A, Vol. 360, No. 4-5, 2007, pp. 582-587. doi:10.1016/j.physleta.2006.08.067 [Citation Time(s):1].
- [8] R. Z. Luo, "Impulsive Control and Synchronization of a New Chaotic System," Physics Letters A, Vol. 372, No. 5, 2008, pp. 648-653. doi:10.1016/j.physleta.2007.08.010 [Citation Time(s):1].
- [9] J. Lu and J. Cao, "Adaptive Complete Synchronization of Two Identical or Different Chaotic (Hyperchaotic) Systems with Fully Unknown Parameters," Chaos, Vol. 15, No. 4, 2005, Article ID: 043901. doi:10.1063/1.2089207 [Citation Time(s):1].
- [10] Z. Jia, "Linear Generalized Synchronization of Chaotic Systems with Uncertain Parameters," Journal of Systems Engineering and Electronics, Vol. 19, No. 4, 2008, pp. 779-784. doi:10.1016/S1004-4132(08)60153-X [Citation Time(s):1].

- [11] M. C. Ho, Y. C. Hung and C. H. Chou, "Phase and Anti-Phase Synchronization of Two Chaotic Systems by Using Active Control," Physics Letters A, Vol. 296, No. 1, 2002, pp. 43-48. doi:10.1016/S0375-9601(02)00074-9 [Citation Time(s):1].
- [12] Y. Chen, X. Chen and S. Chen, "Lag Synchronization of Structurally Nonequivalent Chaotic Systems with Time Delays," Nonlinear Analysis, Vol. 66, No. 9, 2007, pp. 1929-1937. doi:10.1016/j.na.2006.02.033 [Citation Time(s):1].
- [13] M. Hu and Z. Xu, "Nonlinear Feedback Mismatch Synchronization of Lorenz Chaotic Systems," Systems Engineering and Electronics, Vol. 29, No. 8, 2007, pp. 1346-1348. [Citation Time(s):1].
- [14] C. Li and X. Liao, "Lag Synchronization of Rössler System and Chua Circuit via a Scalar Signal," Physics Letters A, Vol. 329, No. 4-5, 2004, pp. 301-308. doi:10.1016/j.physleta.2004.06.077 [Citation Time(s):1].
- [15] C. Li, X. Liao and K. Wong, "Lag Synchronization of Hyperchaos with Application to Secure Communications," Chaos, Solitons & Fractals, Vol. 23, No. 1, 2005, pp. 183-193. doi:10.1016/j.chaos.2004.04.025 [Citation Time(s):1].
- [16] Q. J. Zhang, J. A. Lu and Z. Jia, "Global Exponential Projective Synchronization and Lag Synchronization of Hyperchaotic Lü System," Communications in Theoretical Physics, Vol. 51, No. 4, 2009, pp. 679-683. [Citation Time(s):1].
- [17] Eydelman, S. D., Parabolic System, North. Holan Publishing Company Amsterdam, (1969).
- [18] Mahmoud M. El- Borai, Partial differential equations in an unbounded medium, Academia Nazionale Dei Lincei Series VIII vol. IV December 6, 1973, 657-622.
- [19] Mahmoud M. El- Borai, On the intial value problem for partial differential equations with operator coefficients, Int. J. of Math. And Mathematical Sciences, 3, 1980, pp.103-111.
- [20] Mahmoud M. El – Boria, Generalized random processes and Cauchy's problem for some partial differential equations, Int. J of Math. And mathematical Sc. No. 3, 1980, pp.549-558.
- [21] Mahmoud M. El- Borai, The fundamental solutions for fractional evolution equations of parabolic type, J. of Appl. Math. Stochastic Analysis (JAMSA) 2004, 199-211.
- [22] Mahmoud M. El- Borai, and Khairia El- Said El- Nadi, Osama Labib, Hamdy M., Volterra equations with fractional stochastic integrals, Mathematical problems in Engineering, 5, (2004), 453-468.
- [23] Mahmoud M. El- Borai, and Mohammed I. Abbas, On some integro- differential equations of fractional arders involving caratheodory nonlinearities, Internationa J. of Modern Mathematics, 2 (1) (2007), 41-52.
- [24] Mahmoud M. El- Borai, and Khairia El- Said El- Nadi, A parabolic transform and some stochastic ill- posed problems, British Journal of Mathematics and computer Science, 9 (5), 418-426, 2015.
- [25] Mahmoud M. El- Borai, and Khairia El- Said El- Nadi, Fractional integrated semi groups and nonlocal fractional differential equations, Journal of Progressive Research in Mathematics (JPRM), vol. 5, Issue 3, September 22, 2015, 553-561.
- [26] Mahmoud M. El- Borai, Wagdy G. Elsayed and Ragab M. Al-Masroub, Exact solutions for some nonlinear fractional parabolic equations, International Journal of Advances in Engineering Research, vol. 10, Issue III, September 2015, 106-122.
- [27] Mahmoud M. El- Borai, Wagdy G. Elsayed and Ragab M. Al-Masroub, Exact solutions of some nonlinear complex fractional partial differential equations, international Journal of Mathematics Trends and Technology. (IJMTT), April 2016, vol. 32, No. 1, 4-9.
- [28] Mahmoud M. El- Borai, Wagdy G. Elsayed and Ragab M. Al-Masroub, Exact solutions for time fractional coupled Witham-Boer - Kaup equations via exp- function method, international research Journal of Engineering and Technology (IRJET), September 2015, vol. 2, Issue 6, 307-315.
- [29] Mahmoud M. El- Borai, Wagdy G. Elsayed and Ragab M. Al-Masroub, Exact solutions of some nonlinear partial differential equations via Extended – expansion method, international Journal of Mathematics Trends and Technology, (IJMTT), August 2016, vol 36, No. 1, 60-71.
- [30] Mahmoud M. El- Borai, Wagdy G. Elsayed Adham M. Jawad, Adomian decomposition method for solving fractional differential equations, international Research Journal of Engineering and Technology (IRJET) vol. 2, Issue: 6 September 2015, 296-306.
- [31] Mahmoud M. El- Borai, Wagdy G. Elsayed and Faez N. Ghaffoori, On the solvability of nonlinear integral functional equation, international Journal of Mathematics Trends and Technology, (IJMTT), June 2016, vol. 34, No., 1, 39-44.
- [32] Mahmoud M. El- Borai, Wagdy G. Elsayed and Faez N. Ghaffoori, On the Cauchy problem for some parabolic fractional differential equations with time delays, Journal of Mathematics and system Science, 6, 2016, 194-199.
- [33] Mahmoud M. El- Borai, Wagdy G. Elsayed and Faez N. Ghaffoori, Existence Solution for a fractional nonlinear integral equation of Volterra type, Aryabhatta Journal of Mathematics and informatics, July 2016, vol.8, Issue 2, 1-15.
- [34] Mahmoud M. El- Borai, H. M. El- Owaify, Hamdy M. Ahmed and A. H. Arnous, Soliton Solutions of Hirota equation and Hirota- Maccari system, New Trends in Mathematical Sciences, (NTMSCI), July 2016, vol. 4, No. 3, 231-238.
- [35] M. M. El- Borai, H. M. El- Owaify, Hamdy M. Ahmed and A. H. Arnous, Soliton Solutions of the nonlinear Schrodinger equation by Nonlinear Sci. Lett. A, 2017, 32-40.
- [36] M. M. El- Borai, H. M. El- Owaify, Hamdy M. Ahmed and A. H. Arnous, Seithuti Moshokao, Anjan Biswas, Milivoj Belic, Topological and singular soliton solution to Kundu- Eckhaus equation with extended Kundryashy method, Accepted, International Journal for light and Electron Optics, OPTIK, 2017, 128, 57-62.
- [37] M. M. El- Borai, H. M. El- Owaify, Hamdy M. Ahmed and A. H. Arnous, Seithuti Moshokao, Anjan Biswas, Milivoj Belic, Dark and singular optical solitons solutions with saptio-temporal dispersion, Accepted, Internationa Journal for Light and Electron Optics, November 2016.
- [38] M. M. El- Borai, H. M. El- Owaify, Hamdy M. Ahmed and A. H. Arnous, Exact and Soliton Solutions to nonlinear transmission line model, Nonlinear Dyn. Published online: 16 September 2016.

- [39] J. P. Lasalle, "The Extent of Asymptotic Stability," Proceedings of the National Academy of Sciences of United States of America, Vol. 46, No. 3, 1960, pp. 363-365. dx:10.1073/pnas.46.3.363. [Citation Time(s):1].
- [40] Khairia El-Said El-Nadi, L. M. Fatehy, Nourhan Hamdy Ahmed, Marchall Olkin exponential with application on cancer stem cells, American Journal of Theoretical and Applied Statistics, 2017, 6 (5-1), 1-7.
- [41] Khairia El-Said El-Nadi, On some stochastic differential equations and fractional Brownian motion, International Journal of Pure and Applied Mathematics, Vol. 24, No.3 2005, 416-423.
- [42] Khairia El-Said El-Nadi, Asymptotic methods and some difference fractional differential equations, Int. J. Contemp. Math. sciences, Vol. 1, 2006, 3-14.
- [43] Khairia El-Said El-Nadi, M. M. El-Borai and Eman G. El-Akabawy, On some integro-differential equations of fractional orders, Int. J. Contemp. Math. Sciences, Vol. 2, 2006, No. 15, 719-726.
- [44] Khairia El-Said El-Nadi, M. M. El-Borai and Eman G. El-Akabawy, Approximate solutions for nonlinear fractional heat equations, Int. J. Contemp. Math. Sciences, Vol. 2, 2007, no.27, 1307-1316. Khairia El-Said El-Nadi, On the stability of some stochastic integro partial differential equations, Int. J. Contemp. Math. Sciences, Vol. 2 2007 no. 27, 1317-1326.